

<b>Model Name</b>	<b>SE-1200MU</b>
<b>Product Name</b>	<b>HD 6-Channel Digital Video Switcher</b>
<b>Video Standard</b>	HD
<b>Video Format</b>	1080i 50/59.94/60Hz 720p 50/59.94/60Hz
<b>Video Processing</b>	SDI: 4:2:2 HDMI: YUV 4:2:2 10 bit, RGB 4:4:4
<b>Input Routable / Crosspoint</b>	All 6, repeatable
<b>Video Input</b>	4x HD-SDI 2x HDMI (RGB/YUV, 1080i/1080p/720p)
<b>Mix HD &amp; SD source</b>	N/A
<b>Computer Graphic Interface</b>	2 via HDMI
<b>Video output</b>	2x HD-SDI & 2x HDMI assignable: PGM(w/DSK 1&2), PGM(w/DSK 1), PGM Clean, PVW(w/o DSK), multi-view, Input 1-6
<b>Down-converted output</b>	N/A
<b>Built-in Multi-view monitoring out</b>	HDMI & Ethernet (MJPEG)
<b>Audio input</b>	2x Balanced XLR De-embedded Digital Audio (2 CH)
<b>Audio output</b>	Embedded digital audio (2 CH)
<b>Embedded audio support</b>	embedded 2-CH audio output from XLR input or embedded audio input
<b>Audio Delay Calibration</b>	N/A
<b>A+V switching</b>	Yes
<b>Chromakey</b>	2 Keyers
<b>Title Creator</b>	N/A
<b>USK</b>	2x USK support Chromakey & Linear / Luma Key
<b>DSK</b>	2x DSK support Lumakey & Linear key (Key / Fill)
<b>Picture in Picture</b>	1
<b>Logo Insertion</b>	N/A
<b>Still Store</b>	500

<b>Effects</b>	FTB, Cut, 32 Wipe with border
<b>Transition Preview</b>	Full transitions preview
<b>Sync / Reference In/Out</b>	Built-in Genlock (internal)
<b>Tally Output</b>	1x D-sub 15pin, dual color
<b>PC Remote Control</b>	Via Ethernet (free Window software) or RS-232
<b>Built-in Audio Mixer</b>	N/A
<b>Special Features</b>	Motion JPEG Multi-view streaming (120 memory preset, BGD Transition on/off option) Stinger transition
<b>Chassis</b>	2 units, 1RU rack-mount mainframe
<b>Power</b>	DC 12V 19W
<b>Accessory</b>	CB-60/61/62 (30/50/100m)